Step 1. Put IPv6 F/W of WGSW-24040 in the same folder with **1.dat** & **VSC740X_Update_Tool.exe**.

📛 Update_Tool		
<u>F</u> ile <u>E</u> dit <u>V</u> iew F <u>a</u> vorites	<u>I</u> ools <u>H</u> elp	at 1997 - 1997 - 1997 - 1997 - 1997 - 1997 - 1997 - 1997 - 1997 - 1997 - 1997 - 1997 - 1997 - 1997 - 1997 - 199
🕞 Back 🔹 🌍 👻 🏂	Search 🎼 Folders	
Address C:\Documents and Se	ettings\x\Desktop\Update_Tool	💌 🄁 Go
Make a new folder Publish this folder to the Web Share this folder	WGSW24040_1.5b100524.dat	
Other Places	*	
 Desktop My Documents Shared Documents My Computer My Network Places 		
Details	8	

Step 2. Change IPv6 F/W of WGSW-24040 file name in the 2.dat.



Step 3. Connect RJ-45 & console cable for WGSW-24040 directly which you want to upgrade IPv6 F/W.

Step 4. Double-click VSC740X_Update_Tool.exe. Enable "**Console Monitor**", check local IP address (PC's IP address who has update tool and new F/W) is correct or not and click "**Start**" button to start upgrade F/W.

VSC-740X Update Tool 100623				
RS-232 COM port:	СОМ1 💌	Cor	nsole Monitor	
Username:	admin			
Password:	admin			
Local IP address:	192.168.0.21	-]	
S	tart		Exit	
				_

VSC-740X Update Tool 100623				
RS-232 COM port: COM1 🔽 🔽 Console Monitor				
Username: admin				
Password: admin				
Local IP address: 192.168.0.21				
Start Exit				
conf_sec_open failed or size mismatch, creating defaults W priv_IM 00:00:02 26/VTSS_PRIVILEGE_conf_read_stack#404: Warning: conf_sec_open failed or size mismatch, creating defaults W arp_insp 00:00:02 26/arp_inspection_conf_read_stack#1249: Warning: conf_sec_open failed or size mismatch, creating defaults W ip_guard 00:00:02 26/ip_source_guard_conf_read_stack#1520: Warning: conf_sec_open failed or size mismatch, creating defaults W psec_limit 00:00:02 26/PSEC_LIMIT_cfg_flash_read#491: Warning: conf_sec_open() failed or size mismatch, creating defaults W mvr 00:00:02 26/MVR_conf_read#1613: Warning: conf_sec_open failed or size mismatch, creating defaults W voice_vlan 00:00:02 26/VOICE_VLAN_conf_read_stack#2038: Warning: conf_sec_open failed or size mismatch, creating defaults W voice_vlan 00:00:02 26/VOICE_VLAN_conf_read_stack#2076: Warning: conf_sec_open failed or size mismatch, creating defaults W voice_vlan 00:00:02 26/VOICE_VLAN_conf_read_stack#2076: Warning: conf_sec_open failed or size mismatch, creating defaults W voice_vlan 00:00:02 26/VOICE_VLAN_conf_read_stack#1979: Warning: conf_sec_open failed or size mismatch, creating defaults				

Setp 5. Wait about 5 min, when "**Operation complete window**" is display, the F/W process is upgrade finish.

Infomation 🛛 🛛 🛛		
(į)	Operation complete!	
ĺ.	OK	