Windows Vista Standard TCP/IP Printing Installation

Note: Before this installation, please make sure you have install your printer driver into this properly.



Step1. Double click "printers" icon in the control panel

Step2. Click "Add printers"



Step3. Select "Add a local printer" and click "Next" to continue



Step4. Select "Create a new port" and choose "Standard TCP/IP Port" in the drop-down list

		<u> </u>
G 🖶 Add Printer	mante Battan Communi	a location theory
Choose a printer po	rt	
A printer port is a type of cor printer.	nection that allows your computer to exc	change information with a
O Use an existing port:	LPT1: (Printer Port)	*
Oreate a new port: Type of port:	Local Port	-
	Standard TCP/IP Port	
		Next Cancel

Step5. Please select "Auto detect" in the Device type, key in print server's IP address into "Hostname or IP address" field. Before enter, please make sure your PC and print server are under the same IP segment.

Type a printer nost	
Device type:	TCP/IP Device
Hostname or IP <u>a</u> ddress:	192.168.0.1
Port name:	192.168.0.1
Query the printer and au	tomatically select the driver to use

Step6. Select "Custom" and click "Settings" to enter the detail configuration.

Additional P	ort Information Required	Mond Wilsonier
The detected d 1. The device it 2. The address Either correct th previous wizard	evice is of unknown type. Be sure that: s properly configured. on the previous page is correct. ne address and perform another search on th page or select the device type if you are su	the network by returning to the ure the address is correct.
Device Type		
−Device Type <u>S</u> tandard	Generic Network Card	

Step7. Please select "LPR" in the Protocol, and key-in the "lpt1" in the Queue Name. Click "OK" to continue

Port Settings				
<u>P</u> ort Name:		192.168.0.1		
Printer Name or IP <u>A</u> ddress:		192.168.0.1		
Protocol <u>R</u> aw		-	<u>⊚ L</u> PR	
Raw Settings				
Port <u>N</u> umber:	9100			
LPR Settings	201			
<u>Q</u> ueue Name:	lpt 1			
LPR Byte Counting	Enabled	6		
SNMP Status Enab	oled			
Community Name:	public	ŝ.		
SNMP <u>D</u> evice Index:	1			
	1.00			

There are many kind of port name/number for different printserver. You may refer to your print server manual to know the parameter. If you don't know the parameter, please refer to the table below to try.

	Port 1	Port 2	Port 3
DAW	9100	9101	9102
NAW	9100	9200	9300
	L1	L2	L3
T DD	P1	P2	P3
	LP1	LP2	LP3
	LPT1	LPT2	LPT3

Step8. Select your printer from the list, then click "Next" to continue.

Instan the printer	driver	
Select the manu	facturer and model of your printer. If your printer ca	ame with an installation
disk, click Have	Disk. If your printer is not listed, consult your printer	er documentation for
compatible printe	er sontware.	
Manufacturer	Printers	
HP	HP DeskJet 340 (Monochrome)	
IBM	HP DeskJet 350	1977
	HP DeskJet 350 (Monochrome)	
infotec		
infotec Konica	+ B HP Deskjet 3500 Series	-
infotec Konica	HP Deskjet 3500 Series	-

Step9. Click "Next"

				×
🚱 🖶 🛛 Add Print	er (innersen) (i	Mar Carros	and installe	-
Type a print	er name			
Printer name:	HP Deskjet 3500 Seri	es		
	Set as the <u>d</u> efault	printer		
This printer will be	installed with the HP Desk	get 3500 Series driver.		
			Next	ancel

Step10. Click "Finish"

