

- **Duplex mode support** : Full or half-duplex mode by Auto-Negotiation (TP)
- **LED indicators** : PWR, TX Link/ACT, FX Link/ACT, FDX, 100, FDX
- **Power Requirement** : 5V DC, 2A
- **Ambient Temperature**: 0° to 50°C (operating)
- **Humidity** : 5% to 90% (non-condensing)
- **Dimension** : 26 x 70 x 97mm (HxWxD)
- **Cable:**
 - ⇒ UTP : Cat 5 UTP cable
 - ⇒ Fiber : MM: 50/125 **mm** or 62.5/125 **mm** optic fiber
 - ⇒ Fiber : SM: 8.3/125, 8.7/125, 9/125 **mm** optic fiber

Connecting to Router, Bridge, or Switch, Hub, please refer to the device's Technical Manual.

10. Power information

The power jack of FT-80X is with 2.5mm in the central post and required +5VDC power input. It will conform to the bundled AC-DC adapter and Planet's Media Chassis. Should you have the problem to make the power connection, please contact your local sales representative.

Please keep the AC-DC adapter as spare parts when your FT-80X is installed to a Media Chassis.

Part No.:EM-FT801

