

# Internet Telephony PBX System

**IPX-2000/1800 Series  
Worktime Configuration**



- **Worktime defines holidays and business hours for auto attendant and IVR application. Several groups of date/time could be defined for different IVR menus.**
- **Select Feature -> Worktime to configure Worktime features.**

**:: WORKTIME MANAGEMENT**

Management **Add New**

DEL

	Group ID	Mod	General Worktime	Saturday Worktime	Optional Worktime
<input type="checkbox"/>	<a href="#">222</a>	1	09:00 - 18:00	00:00 - 00:00	10/06 Holiday 10/09 Holiday 10/10 Holiday 10/21 09:00 - 18:00
					1

**1. Click the Add New tab.**

Status: Setup OK!, Return Code : 0

**:: WORKTIME MANAGEMENT**

Management Add New

Worktime Management

Group ID: 100

Mode: 1

General Worktime: 08 : 00 (FROM) 18 : 00 (TO)

Saturday Worktime: 08 : 00 (FROM) 18 : 00 (TO)

Optional Worktime: 01 / 01 (DATE)  Holiday 08 : 00 (FROM) 18 : 00 (TO) ADD

0101 Holiday DEL

**2.** Enter a unique ID containing numbers only.

**3.** Select a Mode for this worktime Group.  
1: No work on weekends.  
2: Work off and on by turns for weekends.  
3: Work half-day on Saturdays.

**4.** Set the general work time from Monday to Friday.

**:: WORKTIME MANAGEMENT**

Management Add New

Worktime Management

Group ID: 100

Mode: 1  
No work on weekends.

General Worktime: 08 : 00 (FROM)  
18 : 00 (TO)

Saturday Worktime: 08 : 00 (FROM)  
18 : 00 (TO)

Optional Worktime: 01 / 01 (DATE)  Holiday  
08 : 00 (FROM)  
18 : 00 (TO) **ADD**

0101 Holiday **DEL**

**ADD**

Status :

5. Set the work time for Saturdays.

6. Set optional worktime for this group if any, and check Holiday as a free day, or it will be regarded as an extra work day.

7. Click **ADD** to submit the optional worktime.

8. Click **ADD** to submit the whole settings.

**:: WORKTIME MANAGEMENT**

Management Add New

DEL

	Group ID	Mode	General Worktime	Saturday Worktime	Optional Worktime
<input type="checkbox"/>	<a href="#">222</a>	1	09:00 - 18:00	00:00 - 00:00	10/06 Holiday 10/09 Holiday 10/10 Holiday 10/21 09:00 - 18:00
<input type="checkbox"/>	<a href="#">300</a>	3	07:00 - 17:00	07:00 - 12:00	
<input type="checkbox"/>	<a href="#">100</a>	1	08:00 - 18:00	08:00 - 18:00	01/01 Holiday 01/02 Holiday
<input type="checkbox"/>	<a href="#">200</a>	2	09:00 - 19:00	09:00 - 19:00	

1

1. Click a group IP to see the edit page.

Status: Setup OK!, Return Code : 0

## :: WORKTIME MANAGEMENT

Management	Add New	Update
<b>Worktime Management</b>		
Group ID	100	
Mode	1 <input type="button" value="v"/> No work on weekends.	
General Worktime	10 <input type="button" value="v"/> : 00 <input type="button" value="v"/> (FROM) 20 <input type="button" value="v"/> : 00 <input type="button" value="v"/> (TO)	
Saturday Worktime	00 <input type="button" value="v"/> : 00 <input type="button" value="v"/> (FROM) 00 <input type="button" value="v"/> : 00 <input type="button" value="v"/> (TO)	
Optional Worktime	01 <input type="button" value="v"/> / 01 <input type="button" value="v"/> (DATE) <input checked="" type="checkbox"/> Holiday 00 <input type="button" value="v"/> : 00 <input type="button" value="v"/> (FROM) 00 <input type="button" value="v"/> : 00 <input type="button" value="v"/> (TO) <input type="button" value="ADD"/>	
	0102 Holiday <input type="button" value="v"/> <input type="button" value="DEL"/>	
	0101 Holiday 0102 Holiday	
<input type="button" value="UPDATE"/>		

**2.** Update the information in this page.

Status : **3.** Click **UPDATE** to submit.

**:: WORKTIME MANAGEMENT**

Management Add New

**DEL**

	Group ID	Mode	General Worktime	Saturday worktime	Optional Worktime
<input type="checkbox"/>	<a href="#">222</a>	1	09:00 - 18:00	00:00 - 00:00	10/06 Holiday 10/09 Holiday 10/10 Holiday 10/21 09:00 - 18:00
<input type="checkbox"/>	<a href="#">300</a>	3	07:00 - 17:00	07:00 - 12:00	
<input type="checkbox"/>	<a href="#">100</a>	1	10:00 - 20:00	00:00 - 00:00	01/01 Holiday 01/02 Holiday
<input type="checkbox"/>	<a href="#">200</a>	2	09:00 - 19:00	09:00 - 19:00	

1

Status: Setup OK!, Return Code : 0

**2. Click DEL to remove this entry.**

**1. Select a group ID and then click DEL to delete this entry.**



# ACTIVATING IP POWER

