

Access method: IO access

Address port: 0x2e

Data port: 0x2f

1.打开WDT

//configuration

Write 87h, 87h to address port

//WDT function

index=07h write07

index=2Dh bit0=0 set to watchdog

index=07h write 08

index=30h write 01

index=F7h write 00

index=F5h bit3=0 second countdown, bit3=1 Minute countdown

index=F6h 0~ff // 倒计时的时间

//Exit

往地址端口写 AAh,

2.shutdown WDT

//进入配置

往地址端口写87h, 87h

//WDT function

index=07h 写 08

index=30h 写 00

//exit

往地址端口写 AAh,