Upgrade Steps

1 Format the USB key to FAT32.

ormat USB Disk (H:)	<u>? ×</u>	USB Disk (H:) Propertie	:5	?
Capacity:		General Tools Hard	ware Sharing	
3.07 GB	-			
<u>File system</u>		- I		
FAT32	-	Type: Local D	Visk	N
Allocation unit size		File system: FAT32		6
Default allocation size	-	📕 Used space:	4,096 bytes	4.00 KB
Volume label	_	Free space:	3,291,852,800 bytes	3.06 GB
		Capacity:	3,291,856,896 bytes	3.06 GB
Format options		4		
🔽 Quick Format				
Enable Compression			Drive H	Disk Cleanup
☐ Create an MS-DOS startup disk			Diven	
·				
1				
Shart Clas	.			1
			OK Cance	Apply

2. Copy the upgrade file to root folder of the usb flash disk(Confirm the file name must end with "*.bin");

🐲 USB Disk (H:)			
Eile Edit View Favorite	es <u>T</u> ools	Help	200
🕝 Back 👻 🕥 👻 🏂	Se 🔎	arch 🦻 Folders 🛛 🎹 🔹	
Address 🥪 H:\			💌 ラ Go
File and Folder Tasks	☆	0480HD.bin BIN File 14,401 KB	
Other Places My Computer My Documents Shared Documents My Network Places	\$		
Details	¥		

3 .Plug in the USB flash disk to DVR; Click(main menu – Hard Disk) to make sure you can see the upgrade file on DVR;

ID	Туре	Size[GB]	Free[GB]	Status	Source
	HDD	998.57G	0.00G	ок	/dev/sda
2	USB	3.31G	3.06G	ок	/dev/sdb
	R.				

4. Click (main menu --upgrade) to upgrade the main board;

Upgrade			(X
MainBoard T	efresh		
Name	File Size	Туре	Date Modified
D480HD.bin	14746533Byte	bin	2013-04-08
1/1			
			RADE Exit

Upgrading...

Upgrade			C	
MainBoard *	efresh			
Name	File Size	Туре	Date Modified	
0480HD bin	14746533Byte	bia	2013-04-08	
W1				
53%		ince	RADE Exit	

Upgrades succeed!



5. Reboot the DVR, and the upgrade finish.